



**T&C**  
Power Conversion

# AG 0313 RF Power Source



**T&C POWER CONVERSION**

**300 Watts RF Power at 13.56 MHz for Industrial and Laboratory Applications.**

## FEATURING:

- Low harmonic level at 300W  $h_{2\leq} -50$  dBc,  $h_3$  and higher  $< -55$  dBc
- Digital Meter, measures forward, reflected and load power simultaneously
- Front Panel Control of Generator and Amplifier functions
- Data acquisition: Status Monitoring & Power Measurement at Analog Port
- RS232 communication: Full Control Of Generator /Amplifier Functions
- AGC Power Leveling: Output Control to better than  $\pm 3$  W of set value.
- Pulse operation



*RF Power Source  
Front Panel View*

The Model AG 0313 is a robust source of RF power for laser modulation, plasma generation, general laboratory and general industrial applications.

Featuring leading edge solid state design for all generator stages, it provides everything for a complete and reliable, controlled RF power delivery system. It reflects the T&C ongoing commitment to provide RF power products of the highest quality, incorporating the current requirements for complete remote control and data acquisition features

### OPERATION

The AG 0313 produces 300W of RF power at a frequency of 13.56 MHz, with low harmonic distortion.

Front Panel offers a LCD display of Forward, Reflected and Load Power readings, RF Status, AGC setups and operating frequency in Generator Mode.

Power meters are calibrated into a 50 Ohm Load and are accurate when unit operates into matched load. Outside of matched condition, the model AG 0313's power measurement system provides an accurate reading of VSWR.

When used as an amplifier, the AG

0313 is compatible with most signal and function generators, computer synthesizer cards and it accurately reproduces all waveforms within its output and bandwidth limits.

The Forced-air cooling system and the internal power supply are designed to permit operation over a wide range of temperature and global AC line conditions.

The AG 0313 is built to withstand a +5 dBm (1.1Vp-p) Input signal. The unit amplifies the inputs of AM, narrow band FM and pulse modulations.


### OUTPUT PROTECTION

AG 0313 is protected by its internal monitoring system for 315 Watts of total Forward Power and 50 Watts of Reflected Power. This will protect the generator output stage from extreme mismatch at the Output.

### GENERAL

T&C's products are designed to be reliable, compact and light in weight. The use of conservatively rated components ensures high reliability and eliminates the need for periodic retuning.

110 Halstead Street  
Rochester, New York 14610  
USA  
Tel: 585.482.5551  
Fax: 585.482.8487  
www.tcpowerconversion.com  
sales@tcpowerconversion.com



# AG 0313 RF Power Source



## Class Of Operation

Class C

## Frequency Of Operation

13.56 MHz

## Frequency Stability

0.005%

## RF Power Output

>300 Watts into 50 Ohm (FWD limit set for 315W)

## Operation as amplifier - optional.

Contact T&C for further details.

**Gain (as amplifier in BURST MGC Mode)** 54 dB @ 100W  $\pm 1$  dB (0dBm IN Drive)

## RF Input Drive(as amplifier in BURST MGC)

Typical range -20 dBm to 0 dBm

## RF Input Drive for AGC

Recommended 0 dBm for the best operation

## Input Drive Source(amplifier)

Signal or function generator, analog input capable of up to 1 Vp-p @ 50 Ohm

## Internal RF Source

Crystal oscillator: 13.56 MHz

## Input and Output Impedance

50 Ohm

**Input VSWR** 1.2:1 max

**Output VSWR** 3:1 max

## Output VSWR Protection

75 Watts max reflected power limit. Automatic, limits typically within 0.5 ms after reverse power reaches 65 Watts or power amplifier current preset limit.

## Harmonic Level @ 300W

Better than -50 dBc for 2-nd harmonic, any other > -55 dBc

## Spurious Output

-55 dBm equivalent noise level at RF Out (generated by internal circuits )

## Mismatch Power Output

Forward power reference to rating:

1.1:1 VSWR (50  $\Omega$ ) up to 315W,  
315W FWD, 175W Load into 2:1,  
180W FWD, 115W Load into 3:1  
115W FWD, 43W Load into 9:1

## Dynamic Power Range

0 to 300W, settings within +/- 2W

## RF Output Settings & Control

- Front Panel EDITOR and function switches for manual control,  
- RS232 port for GUI or other computer communication. Rear Panel.

- SubD 25 Analog and Digital I/O .  
Port power scale 1V=100W. Rear Panel

## Output Blanking/Pulsing

For pulsed applications, T&C amplifiers and generators offer blanking of the output signal for minimum noise RF spectrum. Less than 1 $\mu$ s Rise/Fall time

## Output Control Interfaces (Communications)

SubD 25 Analog and Digital I/O .  
D-COM "Digital Communication" Port: (Optional)  
RS-232  
RS-485  
USB

## Power Monitor Scale Selection

User selectable levels down to 1 watt (in three (3) Scales) within tenths of watt accuracy.

Available scales:

1V=100W

5V=full power

10V=full power

## RF Power Meter accuracy

$\pm 3\%$  typical

## BURST - internal

User settings via GUI and RS232, 485 and USB or custom hardware port settings

## BURST - external

DC to > 200 kHz. User defined BURST scheme via SubD-25. See analog port description for more details.

## RF Power Margin

(Open Loop Max Power/Rated Power)<sup>-1</sup>\*100

50 %

## Rear Panel RF Connectors

INPUT BNC Female

OUTPUT N Female

## AC Power Connection

IEC Standard Power Entry followed by RFI filter. Filter range 0.1 to 30 MHz min.

## AC Circuit Protection

Internally fused on the main DC Power Supply, 15A.

## AC Input Current (RMS)

### RF Out 300W:

100 to 120 VAC - max. I =  $\leq 8.5$  A

200 to 240 VAC - max. I =  $\leq 4$  A

**Maximum: 12A**

Product Features Power Factor Correction (PFC)

## Cooling

Forced air, temperature controlled, heatsink temperature monitored via RS232 GUI interface.

## Acoustic level

45dBa @ Max Fan Speed @ temp.

## Case

Designed to meet EMI and RFI shielding requirements aluminum chassis. Front Panel: plastic overlay with membrane switches.

## Dimensions

H135mm x W211mm x L445mm  
( 5.25" x 8.3" x 17.5" )

## Weight

9 kg, 20 lbs.

## Mounting

Half Rack, 3U high. Optional: Rack Mount Kit, Adapter Kit, Coupling Screws.

## Environmental conditions

**Temp.:** 0° to 40° C ambient

**Humidity:** 80%

Equipment intended for ISM applications in laboratory and light industrial environment.

**T&C Power Conversion, Inc.**

110 Halstead Street, Suite 7

Rochester, NY 14610, USA

Tel: 585-482-5551

Fax: 585-482-8487

www.tcpowerconversion.com

sales@tcpowerconversion.com

**Sales Representative:**