



# T&C Power Conversion, Inc.

110 Halstead Street  
Rochester, New York 14610 USA  
e-mail: sales@TCPowerConversion.com

Phone: 1 585 482 5551  
Fax: 1 585 482 8487

## SUT01LF-5A, STEP-UP (STEP-DOWN) TRANSFORMER FOR IMPEDANCE MATCHING

Most of RF Power Sources are designed and optimized to best deliver power into an impedance of 50 Ohms. In a power delivering system where the source and load impedance differs by more than 2:1 a matching element can improve efficiency.

T&C offers a range of LF Band matching transformers for high and low impedance load applications.

The table below presents some standard impedance ratios offers by T&C.

### CASE OPTIONS:

1. W 4" x L 4" x H 3", deep drawn enclosure, ZERO Corp., #Z64-64A.
2. Custom sizes and configurations on request.
3. Connectors:
  - BNC Input, BNC Outputs

### SPECIFICATIONS

Output Impedance's available. (**Z<sub>in</sub>** = 50 Ohms) Frequency Range 0.2 MHz to 3MHz minimum. Peak performance within 0.4 to 2 MHz. Low power operation possible up to 4 MHz or down to 0.1 MHz (50W max)

<b>Z out</b>	<b>Impedance ratio</b>	<b>Continues P IN</b> (Without cooling)	<b>Max P IN</b>	<b>Peak Voltage</b>
200 ohms	1 : 4	100 W	200 W	~ 400 V p-p @ 100 W
450 ohms	1 : 9	100 W	200 W	~ 600 V p-p @ 100 W
800 ohms	1 : 16	100 W	200 W	~ 800 V p-p @ 100 W
1250 ohms	1 : 25	100 W	200 W	~ 1000 V p-p @ 100 W
1800 ohms	1:36	100W	200W	~ 1200 V p-p @ 100 W

Contact T&C sales office for your custom configurations, quantity prices and delivery schedule.

We offer various electronic products and engineering services: *RF Linear Amplifiers, RF Power Drivers, AC to DC Power Supplies, Microprocessor Based Controllers, Analog Instruments . . .*

**IF YOU CAN'T FIND IT, WE WILL DESIGN IT!**